
## FVD2-2300-NM/1235




## Dipole Antenna

## The most important thing we build is trust

Designed for Broadcast Applications Suitable for Mobile Applications Pattern - Omni Directional Designed for Integrated Solutions Ground Plane Independent





	71]	200 [7.87] RIGID SECTION 456 [17.95] APPROX	
BASE VIEW		Ø26[1.02]	N(M) CONNECTOR

ELECTRICAL		
Frequency	2.20 - 2.40 GHz	
Gain	2 dBi Nom	
Polarisation	Linear (Vertical)	
Beamwidth	360° (Az) x 80° (EI)	
Cross Polar	25 dB	
VSWR	2:1	
Power Rating	25W	
Front to Back	N/A	
MECHANICAL		
Standard Finish	Matt Black	
Mass	180g (0.39 lbs) Approx	
Temperature	-20° to +50°C	
Wind Loading	N/A	
MOUNTING OPTIONS		
Kits Available	N/A	
See separate data sheet	CS .	

European Antennas Limited trading as Cobham Antenna Systems, Microwave Antennas

European Antennas Limited has a policy of continuous development and stress that the information provided is a guide only and does not constitute an offer or contract or part thereof. Whilst every effort is made to ensure the accuracy of the information contained in this brochure, no responsibility can be accepted for any errors or omissions.

GA: 1235

The copyright of antenna designs and images is copyright protected and owned by European Antennas Limited.  $\bigcirc$  European Antennas Limited

Issued 061009

For further information please contact: Cobham Antenna Systems, Microwave Antennas Lambda House, Cheveley, Newmarket, Suffolk CB8 9RG, UK. Tel +44 (0)1638 732 177 Fax +44 (0) 1638 731999  $Email\ newmark et. sales @cobham.com$